



SUBJECT: DS-2500 Special Firmware

PURPOSE: To change the file format from .ds2 to .dss classic and back to default .ds2.


1. **FWUpDssClassic_DS2500.exe:** Changes DS-2500 file format from default .ds2 file to .dss classic file.
2. **FWUpDssPro_DS2500.exe:** Changes DS-2500 file format from .dss classic back to default .ds2 file format.

Note: This firmware is for the DS-2500 only. It is not to be use with the DS-2400.


SOLUTION:

Changing the DS-2500 file format to .dss classic:


1. Download the Special Firmware to your computer in a location you can easily find it. Preferably to a folder you create on your desktop.
2. Extract the files from the folder before you update the firmware in the DS-2500. Not doing so could cause the firmware not to install correctly. After the extraction process has finished you should see two files (FWUpdateDssClassic_DS2500.exe and FWUpdateDssPro_DS2500.exe).



3. Connect the DS-2500 to the computer that has the Special Firmware. If this is the first time the recorder has been connected to the computer, let the computer go through the **found new hardware** process before installing the special firmware.
4. Open the folder containing the special firmware and double left click on the FWUpdateDssClassic_DS2500.exe. You should see the window below: Click on the start button.




5. Once the update is complete, click on the finish button and disconnect the DS-2500.




Changing the DS-2500 Classic file format back to default DS2:

1. Connect the DS-2500 to the computer that has the Special Firmware and open the folder that contains the special firmware.



2. Double left click on the FWUpDssPro_DS2500.exe. You should see the window below:
Click on the start



3. Once the update is complete, click on the finish button and disconnect the DS-2500.

